EWH/EWHS Signal Horn

生産終了 Production end





Original wide horn featuring clear and high volume up to 105dB at 1m, designed for use in noisy environments.

- · 32 sounds are pre-recorded in one unit.
- · For enhanced durability and safety in the work environment.
- · Built-in Alarm: Adjustable audible sound up to 105dB at 1m with volume control.
- · Installation: Indoors—upright, inverted, sideways; Outdoors—upright only. (Do not install the horn facing upward).
- · Easy Installation: With anti-corrosive stainless steel mounting bracket.
- · NPN Compatible: 24V type only (EWH series only).
- · Conforms to the CE requirements (for 12V, 24V type).

Available by Special Order

105dB at 1m

32 sounds

IP65

NPN Open collector


• PNP open collector type.


EWH / EWHS Type

	Model	Rated Voltage	Voltage Range	Power Consumption	Volume	Outer Contact Capacity	Operating Temperature Range	Auxiliary Input	Channel	Protection	Mass		
EWH	EWH-24	12/24V AC/DC	8V~28V AC/9V~35V DC	8W	Max. 105dB at 1m						1.2kg		
	EWH-48	48V DC	35V~60V DC	10W		ı			EWH: Voltage free	8/1bit or		1.2kg	
	EWH-100	100V AC	90V~132V AC	12W			contact	32/binary		1.4kg			
	EWH-200	200V AC	180V~260V AC	13W		105dB at 1m More 10 EWH/I	EW:		8/1bit 32/binary			1.4Kg	
EWHS	EWHS-24	12/24V AC/DC	8V~28V AC/9V~35V DC	8W			105dB at 1m	More than	-20°C~+60°C	32/billary			1.2kg
	EWHS-48	48V DC	35V~60V DC	10W				10mA	Humidity	EWHS:	1	IP53 IP65*	1.2kg
	EWHS-100	100V AC	90V~132V AC	12W				EWH/EWHS:	85% or less.	Voltage contact	'	11 00	1.4kg
	EWHS-200	200V AC	180V~260V AC	13W			More than		Johnadi			1.4Kg	

* By special order

Dimensions







Test switch (for EWH series only)

Test switch is stored under cover. Switch can be used to check the operation or adjust sound volume

Wiring Diagram





Fuse capacity (EWH/EWHS)

Model	Rated Voltage	Fuse
EWH-24/EWHS-24	12-24V	1A (Slow-blow)
EWH-48/EWHS-48	48V	1A (Normal)
EWH-100/EWHS-100	100V	1A (Normal)
EWH-200/EWHS-200	200V	1A (Normal)

8 (Blue) > 7 (Green) > 6 (Orange) > 5 (Red) > 4 (Lightgreen) > 3 (Pink) > 2 (Yellow) > 1 (Skyblue) The greater number has priority when any of the channels are activated simultaneously.

Polarity symbol of power source is for EWH and EWHS series, in 12/24V DC and 48V DC types.

Sound Selection Charts

32 sounds are pre-recorded in one unit. 4 sound types are available.

EWN/EWN9-A					
Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Bell (clear high pitched bell)	Yelp (rapid siren)		
Rapid Hi-Lo	Melody Chime	Synthesized Piano	Synthesized Bell		
Stutter (rapid intermittent horn) Bell (clear high pitched bell)	Synthesized Melody Chime	Chime	Call sign		
Fur Elise	Maiden's Prayer	Minuet	Annie Laurie		
London Bridge is Falling Down	Holdiridia	Mary Had a Little Lamb	Camptown Races		
Kuck kuck	Der Schmied im Walde	On the Bridge of Avignon	Daydream Believer		
Amaryllis	Mozart Symphony No. 40	Itsy Bitsy Spider	Ich bin ein Musikante		
Jeux Interdits	Katuscha	Grandfather's Clock	Ave Maria		

EWH/EWHS-C

Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Bell (clear high pitched bell)	Yelp (rapid siren)		
Rapid Hi-Lo	Melody Chime	Synthesized Piano	Synthesized Bell		
Stutter (rapid intermittent horn) Bell (clear high pitched bell)	Synthesized Melody Chime	Chime	Ca ll sign		
Can't Take My Eyes off of You	Top of the World	The Entertainer	Amazing Grace		
Amairono Kamino Otome	Les Champs-Elysees	Canon	Rara Sanshain		
Uchuusenkan Yamato	Oshiete	Makenaide	Gonna Fly Now (Theme for "Rocky")		
I Don't Want to Miss a Thing	Yozorano Mukou	Aiwa Katsu	Haruyo Koi		
Gattsudaze	Odoru Ponpokorin	Imasugu Kisu Mi	Truth		

T-0710139 T-0710140

EWH/EWHS-D

Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Bell (clear high pitched bell)	Yelp (rapid siren)
Rapid Hi-Lo	Melody Chime	Synthesized Piano	Synthesized Bell
Runner	Mamotte Agetai	Chime	Ca ll sign
Oribiao Kikinagara	A September	Doyoubino Koibito	Akino Kehai
Saafu Tengoku Sukii Tengoku	Iro Howaitoburendo	Happy Birthday	Hi Ho
I've been working on the Railroad	Bear Song	Toys Go Cha Cha Cha	Konnako Irukana
Wiegenlied	Rudolph the Red-nosed Reindeer	She Wore a Yellow Ribbon	Oh My Darling Clementine
Yellow Rose of Texas	Yankee Doodle	When the Saints Go Marching In	Londonderry Air

EWH/EWHS-E

Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Inverted Receille	Annie Laurie
Stutter (rapid intermittent horn)	Synthesized Melody Chime	Galactic Motor	London Bridge is Falling Down
Bell (clear high pitched bell)	Chime	Ringing Phone	Mary Had a Little Lamb
Yelp (rapid siren)	Call Sign	Two Tone	Camptown Races
Rapid Hi-Lo	Train Ride	Alarm Clock	Amary ll is
Melody Chime	Galloping Hi-Lo	Ringing Hi-Lo	Mozart Symphony No.40
Synthesized Piano	Alien Chatter	Fur Elise	Ave Maria
Synthesized Bell	Falling Crystals	Minuet in G	Grandfather's Clock

PATLITE Corporation has not applied for permission to use certain copyrighted music or songs recorded in EWH/EWHS-A, C and D types outside of Japan. Therefore, please contact the local copyright association for permission before using the product in case this product is used outside of Japan. EWH/EWHS-E type is recommended for use outside of Japan as this model does not include copyrighted music or songs, and permission is